



## TECHNICAL SPECIFICATIONS

Model Number	AC Input		Phase	Battery Voltage	AH Capacity 3 Hrs.	Max Current Output	Input Cable (min)	Ground Wire (min)	Battery Cables	Wt./ Lbs.	Dimensions
	Voltage	Amps									
ATR3010-24-480	480	7	3	24	360-540	180	3 x 10	10	2/0	133	37 x 16.2 x 12.5
	480	11	3	36	360-540	180	3 x 10	10	2/0	133	
	480	15	3	48	360-540	180	3 x 10	10	2/0	133	
ATR3010-24-600	600	6	3	24	360-540	180	3 x 10	10	2/0	133	37 x 16.2 x 12.5
	600	9	3	36	360-540	180	3 x 10	10	2/0	133	
	600	12	3	48	360-540	180	3 x 10	10	2/0	133	
ATR3015-24-480	480	11	3	24	360-780	260	3 x 8	10	2/0	133	37 x 16.2 x 12.5
	480	16	3	36	360-780	260	3 x 8	10	2/0	133	
	480	20	3	48	360-780	250	3 x 8	10	2/0	133	
ATR3015-24-600	600	8	3	24	360-780	260	3 x 8	10	2/0	133	37 x 16.2 x 12.5
	600	13	3	36	360-780	260	3 x 8	10	2/0	133	
	600	16	3	48	360-780	250	3 x 8	10	2/0	133	
ATR3020-24-480	480	14	3	24	360-1050	350	3 x 6	10	3/0	155	33.8 x 28.7 x 27.4
	480	21	3	36	360-1050	350	3 x 6	10	3/0	155	
	480	28	3	48	360-1050	350	3 x 6	10	3/0	155	



P.O. Box 808 • 9404 Ooltewah Industrial Drive  
 Ooltewah, TN 37363 USA  
 Tel: 423 238 5700 • 800 238 VOLT (8658)  
[www.hawkerpowersource.com](http://www.hawkerpowersource.com)

Model Number	AC Input		Phase	Battery Voltage	AH Capacity 3 Hrs.	Output Voltage	Input Cable (min)	Ground Wire (min)	Battery Cables	Wt./ Lbs.	Dimensions
	Voltage	Amps									
ATR3020-40-480	480	19	3	48	360-690	230	3 x 6	10	2/0	155	33.8 x 28.7 x 27.4
	480	26	3	72	360-630	210	3 x 6	10	2/0	155	
	480	28	3	80	360-630	210	3 x 6	10	2/0	155	
ATR3030-24-480	480	20	3	24	360-1500	500	3 x 6	10	2 x 2/0	264	33.8 x 28.7 x 27.4
	480	30	3	36	360-1500	500	3 x 6	10	2 x 2/0	264	
	480	41	3	48	360-1500	500	3 x 6	10	2 x 2/0	264	
ATR3030-40-480	480	26	3	48	360-960	320	3 x 6	10	3/0	264	33.8 x 28.7 x 27.4
	480	38	3	72	360-930	310	3 x 6	10	3/0	264	
	480	42	3	80	360-930	310	3 x 6	10	3/0	264	

NOTES:

1. AC input voltage  $\pm 10\%$
2. Frequency Hz 50/60
3. Battery Cable Length: 3 to 33 ft.
4. IP Protection IP20
5. Operating Temperature 32 to 104°F
6. Display – LCD
7. All ATR Chargers require either an SBX 350 or Euro 320 connector for arc less protection, and to meet the Ah output capacity specifications.
8. The ATR 3020-24-480 (24v, 36v, 48v) all three require the use of an SBX 350 connector on the charger and battery.
9. The ATR 3030-24-480 (24v, 36v, 48v) all three require the use of DUAL CABLE LEADS and CONNECTORS on the charger and battery.